

SOFT STARTER, ADX... TYPE, FOR SEVERE DUTY (STARTING CURRENT 5•IE). WITH INTEGRATED BY-PASS CONTACTOR, 60A

| | | | | and a second |
|--------------------------|------------------------|--|-----|--|
| Product designation | • | | | Soft Starter |
| Product type designat | lon | | | ADXB Asynchronous |
| Motor type | | | | three phase |
| Electrical features | | | | |
| Supplies voltage | | Type of avetem | | Three phase |
| | | Type of system | V | Three phase 208500VAC |
| | | Rated supply voltage | V | 208240VAC |
| | | auxiliary supply voltage (Us) Rated frequency | Hz | 50/60 |
| Rated starter current I | 0 | Nated frequency | A | 60 |
| Rated motor power | <u> </u> | | | |
| realed motor power | IEC ratings (T≤40°C) | | | |
| | inco ratings (1340 C) | 230VAC | kW | 15 |
| | | 400VAC | kW | 30 |
| | | 500VAC | KW | 37 |
| | UL ratings (T≤40°C) | 0001710 | | |
| | 02 ramige (1 = 10 ° 0) | 220-240VAC | HP | 20 |
| | | 380-415VAC | HP | 30 |
| | | 440-480VAC | HP | 40 |
| Number of controlled | phases | | Nr. | 3 |
| Built-in bypass | • | | | Yes |
| Cooling System | | | | Forced |
| Programming interfac | e | | | |
| | | | | Backlit LCD 2x16 |
| Display | | | | character |
| Programming with NF | C technology | | | No |
| Optical port | | | | No |
| Startup and stop settir | ngs | | | |
| Startup method | | | | Torque or voltage ramp with current limitation |
| Stop method | | | | Torque ramp, voltage ramp, free-wheel stop |
| Braking method | | | | DC dynamic with external relay |
| Protections | | | | |
| Auxiliary supply protect | ction | | | Voltage too low |
| Power supply Protecti | ion | | | No power, phase loss, phase sequence, frequency out of limits, minimum |
| | | | | and maximum |

voltage





51ADX0060B

SOFT STARTER, ADX... TYPE, FOR SEVERE DUTY (STARTING CURRENT 5•IE). WITH INTEGRATED BY-PASS CONTACTOR, 60A

| Motor protection | | Overload at starting (trip class 2, 10A, 10, 15, 20, 25, 30, 35 and 40), overload during running (trip class 2, 10A, 10, 15, 20, 25 and 30), locked rotor, current asymmetry, minimum torque (dry run), |
|--|-----------------------------|---|
| Starter protection Functions | | Overcurrent, overtemperature, bypass failure, phase shorted, temperature sensor fault, maintenance request |
| Built-in bypass | | 3 |
| Built-in display and keypad | | Yes |
| Languages | | Yes |
| View measurements | | 4 |
| Torque control | | Yes |
| Adjustable current limit | | Yes |
| Dynamic braking | | Yes |
| Kick Start function | | Yes |
| Motor overload electronic protection | | Yes |
| Motor protection PTC input | | Yes |
| Protection against phase loss | | Yes |
| Protection against phase inversion | | Yes |
| Protection against locked rotor | | Yes |
| Protection against thyristor overtemperature | | Yes |
| Protection against low load | | Yes |
| Programmable alarm | | Yes |
| Digital inputs | | Yes |
| Analog inputs | | Yes |
| Digital outputs | | Yes |
| Analog output | | Yes |
| Monitoring communication | | Yes |
| Optical port for programming | | RS323 |
| Event log | | No |
| Motor hour counter | | Yes |
| Startup counter | | Yes |
| Clock calendar | | Yes |
| Remote external keypad | | Yes |
| Plug-in version | | Optional |
| Input and Output | | |
| Digital inputs | | |
| | Number of digital input Nr. | 3 (2 digital inputs + 1 digital/analog |

input)





SOFT STARTER, ADX... TYPE, FOR SEVERE DUTY (STARTING CURRENT 5•IE). WITH INTEGRATED BY-PASS CONTACTOR, 60A

| Analog inputs | Digital input type Digital input functions | 24VDC (no r for external feeder) 1 input for sta input programmab (stop, free-w stopping, ext alarm, motor preheat, loca control, alarm inhibit, manual resetting of r thermal protection, keypad lock, second motor | art, 1 ple wheel ternal al ms al motor |
|-----------------|---|--|---|
| Analog inputs | Number of analog input | Nr. 1 (digital/ana 0-10VDC (0- | |
| | Analog input type | 20mA with external resis 500Ω) Motor protec via PTC prot acceleration and/or deceleration ramp via ana | stor etion bes, |
| | Analog input functions | input, analog input thresho for motor sta and stopping analog input thresholds for programmab relay enable | olds arting g, or ole |
| Digital outputs | Number of digital output | Nr. 4 | |
| | Digital output arrangement | 3 x 1 NO (SF + 1 C/O (SP) Ratings: 5A 250VAC AC 250VAC AC | DT) 1, 2A 15 |
| Analog outputs | Digital output functions | C/O output for global alarm, 1NO outputs programmab (OFF, motor powered, up speed, brakin current limit, service required cascade star programmab input threshot alarm Axx) | , 3 x ble to ng, ired, rting, ble |

51ADX0060B



SOFT STARTER, ADX... TYPE, FOR SEVERE DUTY (STARTING CURRENT 5•IE). WITH INTEGRATED BY-PASS CONTACTOR, 60A

Number of analog output Nr.

0...20mA,

Analog output type

4...20mA (0...10V with external resistor 500Ω) Current, torque,

motor thermal status, power

Analog output functions

factor and active

power

Ambient conditions

Temperature

Operating temperature

°C min -10

+55°C (with current derating max

>45°C of 1.5%/

°C)

Storage temperature

°C min -30 °C +70 max

m

1000 without


derating (over 1000mt with current derating

of 0.5%/100m) 95% without Relative humidity % condensation or dripping

Pollution degree 3

Max altitude

| Housing | | |
|-------------------------|----|-----------------|
| Mounting | | Screw-fixing |
| IP degree of protection | | IP20 |
| Dimensions (W x H x D) | mm | 157 x 534 x 250 |
| Weight | Kg | 14.2 |



| TYPE | A | В | С | D | E |
|-----------|-------------|--------------|-------------|-------------|--------------|
| ADX 0017B | 157 (6.18") | 372 (14.64") | 223 (8.78") | 131 (5.16") | 357 (14.05") |
| ADX 0030B | 157 (6.18") | 372 (14.64") | 223 (8.78") | 131 (5.16") | 357 (14.05") |
| ADX 0045B | 157 (6.18") | 372 (14.64") | 223 (8.78") | 131 (5.16") | 357 (14.05") |
| ADX 0060B | 157 (6.18") | 534 (21.02") | 250 (9.84") | 132 (5.20") | 517 (20.35") |
| ADX 0075B | 157 (6.18") | 534 (21.02") | 250 (9.84") | 132 (5.20") | 517 (20.35") |
| ADX 0085B | 157 (6.18") | 534 (21.02") | 250 (9.84") | 132 (5.20") | 517 (20.35") |
| ADX 0110B | 157 (6.18") | 584 (22.99") | 250 (9.84") | 132 (5.20") | 567 (22.32") |
| ADX 0125B | 157 (6.18") | 584 (22.99") | 250 (9.84") | 132 (5.20") | 567 (22.32") |

Certifications and compliance

Compliance

IEC/EN 60947-1



51ADX0060B

SOFT STARTER, ADX... TYPE, FOR SEVERE DUTY (STARTING CURRENT 5•IE). WITH INTEGRATED BY-PASS CONTACTOR, 60A

IEC/EN 60947-4-2

Certificates

EAC

ETIM classification

ETIM 8.0 EC000640 - Soft starter