## **DATASHEET - BZMB1-4-A20-BT**



Circuit-breaker, 4 p, 20A, box terminal

Part no. BZMB1-4-A20-BT Catalog No. 112548 Alternate Catalog BZMB1-4-A20-BT No.



Similar to illustration

**Design verification as per IEC/EN 61439** 

| Design verincation as per 126/214 01433  |                  |   |  |
|--|------------------|---|--|
| Technical data for design verification   |                  |   |  |
| Rated operational current for specified heat dissipation   | In               | Α | 20   |
| Equipment heat dissipation, current-dependent  | P <sub>vid</sub> | W | 4.7  |
| IEC/EN 61439 design verification   |                  |   |  |
| 10.2 Strength of materials and parts   |                  |   |  |
| 10.2.2 Corrosion resistance  |                  |   | Meets the product standard's requirements.   |
| 10.2.3.1 Verification of thermal stability of enclosures   |                  |   | Meets the product standard's requirements.   |
| 10.2.3.2 Verification of resistance of insulating materials to normal heat   |                  |   | Meets the product standard's requirements.   |
| 10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects |                  |   | Meets the product standard's requirements.   |
| 10.2.4 Resistance to ultra-violet (UV) radiation   |                  |   | Meets the product standard's requirements.   |
| 10.2.5 Lifting   |                  |   | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.2.6 Mechanical impact   |                  |   | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.2.7 Inscriptions  |                  |   | Meets the product standard's requirements.   |
| 10.3 Degree of protection of ASSEMBLIES  |                  |   | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.4 Clearances and creepage distances   |                  |   | Meets the product standard's requirements.   |
| 10.5 Protection against electric shock   |                  |   | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.6 Incorporation of switching devices and components   |                  |   | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.7 Internal electrical circuits and connections  |                  |   | Is the panel builder's responsibility.   |
| 10.8 Connections for external conductors   |                  |   | Is the panel builder's responsibility.   |
| 10.9 Insulation properties   |                  |   |  |
| 10.9.2 Power-frequency electric strength   |                  |   | Is the panel builder's responsibility.   |
| 10.9.3 Impulse withstand voltage   |                  |   | Is the panel builder's responsibility.   |
| 10.9.4 Testing of enclosures made of insulating material   |                  |   | Is the panel builder's responsibility.   |
| 10.10 Temperature rise   |                  |   | The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. |
| 10.11 Short-circuit rating   |                  |   | Is the panel builder's responsibility. The specifications for the switchgear must lobserved.                                     |
| 10.12 Electromagnetic compatibility  |                  |   | Is the panel builder's responsibility. The specifications for the switchgear must observed.                                      |
| 10.13 Mechanical function  |                  |   | The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.                         |

## **Technical data ETIM 7.0**

Low-voltage industrial components (EG000017) / Power circuit-breaker for trafo/generator/installation protection (EC000228)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Circuit breaker for power transformer, generator and system protection (ecl@ss10.0.1-27-37-04-09 [AJZ716013])

| Α  | 20                                       |
|----|--|
| V  | 415 - 415                                |
| kA | 25                                       |
| Α  | 0 - 0                                    |
| Α  | 0 - 0                                    |
| Α  | 256 - 384                                |
|    | No                                       |
|    | Frame clamp                              |
|    | Built-in device fixed built-in technique |
|    | No                                       |
|    | V<br>kA<br>A<br>A                        |