DATASHEET - MMCM-B16/1



Miniature circuit breaker (MCB), 16 A, 1p, characteristic: B

Part no. mMCM-B16/1 Catalog No. 138865



Delivery program

Basic function			Miniature circuit-breakers
Number of poles			1 pole
Tripping characteristic			В
Application			Switchgear for residential and commercial applications
Rated current	In	Α	16
Rated switching capacity according to IEC/EN 60898-1	I _{cn}	kA	10
Product range			mMCM

Technical data

Electrical

I _{cn}	kA	10
Ui	V	440
U_{imp}	kV	4
Operations		≧ 10000
Operations		≧ 20000
	U _i U _{imp} Operations	U _i V U _{imp} kV

References

Auxiliary switch for subsequent installation	ZP-IHK 286052
Tripping signal contact for subsequent installation	ZP-NHK 248437
Remote control and automatic switching device	Z-FW/LP 248296
Switching interlock	Z-IS/SPE-1TE 274418

Mechanical

Standard front dimension	mm	45
Device height	mm	80
Mounting		Quick attachment with 3 latch positions for top-hat rail IEC/EN 60715
Degree of Protection		IP20
Terminals top and bottom		Open mouthed/lift terminals
Terminal protection		BGV A3, ÖVE-EN 6
Thickness of busbar material	mm	0.8 - 2

Design verification as per IEC/EN 61439

Technical data for design verification			
Rated operational current for specified heat dissipation	In	Α	16
Heat dissipation per pole, current-dependent	P_{vid}	W	0
Equipment heat dissipation, current-dependent	P_{vid}	W	2.2
Static heat dissipation, non-current-dependent	P_{vs}	W	0
Heat dissipation capacity	P _{diss}	W	0
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	75
			linear, per +1 °C, results in a 0.5% reduction of current carrying capacity
IEC/EN 61439 design verification			
10.2 Strength of materials and parts			
10.2.2 Corrosion resistance			Meets the product standard's requirements.

observed.		
10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects 10.2.4 Resistance to ultra-violet (UV) radiation 10.2.5 Lifting Does not apply, since the entire switchgear needs to be evaluated. 10.2.6 Mechanical impact 10.2.7 Inscriptions Meets the product standard's requirements. 10.3 Degree of protection of ASSEMBLIES Does not apply, since the entire switchgear needs to be evaluated. 10.4 Clearances and creepage distances Meets the product standard's requirements. 10.5 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 10.6 Incorporation of switching devices and components Does not apply, since the entire switchgear needs to be evaluated. 10.6 Incorporation of switching devices and components Does not apply, since the entire switchgear needs to be evaluated. 10.7 Internal electric alcircuits and connections Is the panel builder's responsibility. 10.8 Connections for external conductors Is the panel builder's responsibility. 10.9.1 Insulation properties 10.9.2 Power-frequency electric strength Is the panel builder's responsibility. 10.9.3 Impulse withstand voltage Is the panel builder's responsibility. 10.9.4 Testing of enclosures made of insulating material Is the panel builder's responsibility. 10.10 Temperature rise The panel builder's responsibility. The specifications for the switchgear must be observed. 10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.2.3.1 Verification of thermal stability of enclosures	Meets the product standard's requirements.
and fire due to internal electric effects 10.2.4 Resistance to ultra-violet (UV) radiation 10.2.5 Lifting 10.2.6 Mechanical impact 10.2.7 Inscriptions 10.2.7 Inscriptions 10.2.8 Mechanical impact 10.2.7 Inscriptions 10.3 Degree of protection of ASSEMBLIES 10.4 Clearances and creepage distances 10.5 Protection against electric shock 10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9 Power-frequency electric strength 10.9.2 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.13 Mechanical function Meets the product standard's requirements. 10.6 Does not apply, since the entire switchgear needs to be evaluated. 10.7 Internal electrical circuits and connections 10.8 List the panel builder's responsibility. 10.9 Insulation properties 10.9.1 Temperature rise 10.9.2 Power-frequency electric strength 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.13 Mechanical function 10.14 Meets the product standard's requirements. 10.15 Meets the product standard's requirements. 10.16 Meets the product standard's requirements. 10.17 Internal electrical circuits and connections 10.18 List the panel builder's responsibility. 10.19 List the panel builder's responsibility. 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function	10.2.3.2 Verification of resistance of insulating materials to normal heat	Meets the product standard's requirements.
10.2.5 Lifting 10.2.6 Mechanical impact 10.2.6 Mechanical impact 10.2.7 Inscriptions 10.3 Degree of protection of ASSEMBLIES 10.3 Degree of protection of ASSEMBLIES 10.4 Clearances and creepage distances 10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9 Power-frequency electric strength 10.9.1 Sullation properties 10.9.2 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.13 Mechanical function 10.14 Mechanical function 10.15 Mechanical function 10.16 meets the entire switchgear needs to be evaluated. 10.10 Temperature rise possibility. 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.14 Mechanical function 10.15 Mechanical function 10.16 meets the entire switchgear needs to be evaluated. 10.17 Internal electric strength against electric strength and the entire switchgear needs to be evaluated. 10.18 Mechanical function 10.19 Insulation properties 10.10 Temperature rise 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.14 Mechanical function 10.15 Mechanical function 10.16 Mechanical function 10.17 Mechanical function 10.18 Mechanical function 10.19 Mechanical function 10.19 Mechanical function 10.10 Temperature rise entire switchgear must be observed. 10.11 Mechanical function 10.19 Mechanical function 10.19 Mechanical function 10.10 Temperature file entire switchgear must be observed. 10.11 Mechanical function		Meets the product standard's requirements.
10.2.6 Mechanical impact 10.2.7 Inscriptions Meets the product standard's requirements. 10.3 Degree of protection of ASSEMBLIES Does not apply, since the entire switchgear needs to be evaluated. 10.4 Clearances and creepage distances Meets the product standard's requirements. 10.5 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 10.6 Incorporation of switching devices and components Does not apply, since the entire switchgear needs to be evaluated. 10.7 Internal electrical circuits and connections Is the panel builder's responsibility. 10.8 Connections for external conductors Is the panel builder's responsibility. 10.9 Insulation properties 10.9.2 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.10 Themperature rise The panel builder's responsibility. 10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.12 Electromagnetic compatibility The device meets the requirements, provided the information in the instruction	10.2.4 Resistance to ultra-violet (UV) radiation	Meets the product standard's requirements.
10.2.7 Inscriptions Meets the product standard's requirements. 10.3 Degree of protection of ASSEMBLIES Does not apply, since the entire switchgear needs to be evaluated. 10.4 Clearances and creepage distances Meets the product standard's requirements. 10.5 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 10.6 Incorporation of switching devices and components Does not apply, since the entire switchgear needs to be evaluated. 10.7 Internal electrical circuits and connections Is the panel builder's responsibility. 10.8 Connections for external conductors Is the panel builder's responsibility. 10.9.1 Insulation properties 10.9.2 Power-frequency electric strength 10.9.3 Impulse withstand voltage Is the panel builder's responsibility. 10.9.4 Testing of enclosures made of insulating material Is the panel builder's responsibility. 10.10 Temperature rise The panel builder's responsibility. The specifications for the switchgear must be observed. 10.12 Electromagnetic compatibility 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.2.5 Lifting	Does not apply, since the entire switchgear needs to be evaluated.
Does not apply, since the entire switchgear needs to be evaluated. 10.4 Clearances and creepage distances Meets the product standard's requirements. 10.5 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 10.6 Incorporation of switching devices and components Does not apply, since the entire switchgear needs to be evaluated. 10.7 Internal electrical circuits and connections Is the panel builder's responsibility. 10.8 Connections for external conductors Is the panel builder's responsibility. 10.9 Insulation properties 10.9.2 Power-frequency electric strength 10.9.3 Impulse withstand voltage Is the panel builder's responsibility. 10.9.4 Testing of enclosures made of insulating material Is the panel builder's responsibility. 10.10 Temperature rise The panel builder is responsibility. The specifications for the switchgear must be observed. 10.12 Electromagnetic compatibility 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.2.6 Mechanical impact	Does not apply, since the entire switchgear needs to be evaluated.
Meets the product standard's requirements. 10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9 Insulation properties 10.9.2 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Is the panel builder's responsibility. In provide heat dissipation data for the temperature rise calculation. Eaton will provide heat dissipation for the temperature rise observed. In the panel builder's responsibility. The specifications for the switchgear must be observed. In the device meets the requirements, provided the information in the instruction.	10.2.7 Inscriptions	Meets the product standard's requirements.
Does not apply, since the entire switchgear needs to be evaluated. 10.6 Incorporation of switching devices and components Does not apply, since the entire switchgear needs to be evaluated. 10.7 Internal electrical circuits and connections Is the panel builder's responsibility. 10.8 Connections for external conductors Is the panel builder's responsibility. 10.9.1 Insulation properties 10.9.2 Power-frequency electric strength Is the panel builder's responsibility. 10.9.3 Impulse withstand voltage Is the panel builder's responsibility. 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating Is the panel builder is responsibility. The specifications for the switchgear must be observed. 10.12 Electromagnetic compatibility 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.3 Degree of protection of ASSEMBLIES	Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9 Insulation properties 10.9.2 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function Does not apply, since the entire switchgear needs to be evaluated. Is the panel builder's responsibility. Is the panel builder's responsibility. Is the panel builder's responsibility. The panel builder is responsibility. Is the panel builder is responsibility. The specifications for the switchgear must be observed. Is the panel builder's responsibility. The specifications for the switchgear must be observed. Is the panel builder's responsibility. The specifications for the switchgear must be observed. The device meets the requirements, provided the information in the instruction	10.4 Clearances and creepage distances	Meets the product standard's requirements.
10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9 Insulation properties 10.9.2 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function Is the panel builder's responsibility. Is the panel builder's responsibility. Is the panel builder is responsibility. The specifications for the switchgear must be observed. In the panel builder's responsibility. The specifications for the switchgear must be observed. In the device meets the requirements, provided the information in the instruction	10.5 Protection against electric shock	Does not apply, since the entire switchgear needs to be evaluated.
10.8 Connections for external conductors 10.9 Insulation properties 10.9.2 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 1 Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function 1 Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.15 Mechanical function 1 Is the panel builder's responsibility. The specifications for the switchgear must be observed. 1 Is the panel builder's responsibility. The specifications for the switchgear must be observed.	10.6 Incorporation of switching devices and components	Does not apply, since the entire switchgear needs to be evaluated.
10.92 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.13 Mechanical function Is the panel builder's responsibility. Is the panel builder is responsibility. The panel builder is responsibility at the temperature rise calculation. Eaton will provide heat dissipation data for the devices. Is the panel builder's responsibility. The specifications for the switchgear must be observed. The device meets the requirements, provided the information in the instruction	10.7 Internal electrical circuits and connections	Is the panel builder's responsibility.
10.9.2 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.13 Mechanical function 10.14 Is the panel builder's responsibility. 15 the panel builder's responsibility. 16 the panel builder's responsibility. The specifications for the switchgear must be observed. 17 the panel builder's responsibility. The specifications for the switchgear must be observed. 18 the panel builder's responsibility. The specifications for the switchgear must be observed. 19 the panel builder's responsibility. The specifications for the switchgear must be observed. 10 the device meets the requirements, provided the information in the instruction	10.8 Connections for external conductors	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.13 Mechanical function 10.14 Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.15 Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.15 Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.16 Is the panel builder's responsibility. The specifications for the switchgear must be observed.	10.9 Insulation properties	
10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise The panel builder is responsibility. The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. 10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.10 Temperature rise The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. 10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
provide heat dissipation data for the devices. 10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
observed. 10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.10 Temperature rise	
observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
	10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
	10.13 Mechanical function	

Technical data ETIM 7.0

Circuit breakers and fuses (EG000020) / Miniature circuit breaker (MCB) (EC000042)

Electric engineering, automation, process control engineering / Electrical installation, device / Miniature circuit breaker system (MCB) / Miniature circuit breaker (MCB) (ecl@ss10.0.1-27-14-19-01 [AAB905014])

			n.
Release characteristic			В
Number of poles (total)			1
Number of protected poles			1
Rated current	А	L	16
Rated voltage	V		230
Rated insulation voltage Ui	V		440
Rated impulse withstand voltage Uimp	kV	V	4
Rated short-circuit breaking capacity Icn EN 60898 at 230 V	k#	A	10
Rated short-circuit breaking capacity Icn EN 60898 at 400 V	k.A	A	10
Rated short-circuit breaking capacity Icu IEC 60947-2 at 230 V	k#	A	15
Rated short-circuit breaking capacity Icu IEC 60947-2 at 400 V	k#	A	15
Voltage type			AC
Frequency	Hz	z	50 - 60
Current limiting class			3
Suitable for flush-mounted installation			No
Concurrently switching N-neutral			No
Over voltage category			3
Pollution degree			2
Additional equipment possible			Yes
Width in number of modular spacings			1
Built-in depth	m	ım	70.5
Degree of protection (IP)			IP20
Ambient temperature during operating	°C	С	-25 - 75
Connectable conductor cross section multi-wired	m	nm²	1 - 25
Connectable conductor cross section solid-core	m	nm²	1 - 25