DATASHEET - NZMB1-1-AF32



Circuit-breaker, 1p, 32A

Part no. NZMB1-1-AF32 Catalog No. 152533 Alternate Catalog NZMB1-1-AF32



Delivery program

Delivery program			
Product range			Circuit-breaker
Protective function			System and cable protection
Standard/Approval			IEC
Installation type			Fixed
Release system			Thermomagnetic release
Construction size			NZM1
Description			Fixed overload releases Ir
Number of poles			1 pole
Standard equipment			Box terminal
Switching capacity			
400/415 V 50 Hz	I _{cu}	kA	25
Rated current = rated uninterrupted current			
Rated current = rated uninterrupted current	$I_n = I_u$	Α	32
Setting range			
Overload trip			
4	l _r	Α	32 - 32
Short-circuit releases			
Non-delayed	$I_i = I_n \times \dots$		340 A fixed

Technical data

General

delicitui			
Standards			IEC/EN 60947
Protection against direct contact			Finger and back of hand proof to VDE 0106 Part 100
Climatic proofing			Damp heat, constant, to IEC 60068-2-78 Damp heat, cyclic, to IEC 60068-2-30
Ambient temperature			
Ambient temperature, storage	c	°C	- 40 - + 70
Operation	c	°C	-25 - +70
Mechanical shock resistance (10 ms half-sinusoidal shock) according to IEC 60068-2-27	Ç	g	20 (half-sinusoidal shock 20 ms)
Safe isolation to EN 61140			
Between auxiliary contacts and main contacts	\	V AC	500
between the auxiliary contacts	\	V AC	300
Mounting position			Vertical and 90° in all directions

			With XFI earth-fault release: - NZM1, N1, NZM2, N2: vertical and 90° in all directions with plug-in unit - NZM1, N1, NZM2, N2: vertical, 90° right/left with withdrawable unit: - NZM3, N3: vertical, 90° right/left - NZM4, N4: vertical with remote operator: - NZM2, N(S)2, NZM3, N(S)3, NZM4, N(S)4: vertical and 90° in all directions
Direction of incoming supply			as required
Degree of protection			
Device Enclosures			In the operating controls area: IP20 (basic degree of protection) With insulating surround: IP40 With door coupling rotary handle: IP66
Terminations			Tunnel terminal: IP10 Phase isolator and strip terminal: IP00
Other technical data (sheet catalogue)			Weight Temperature dependency, Derating Effective power loss
Circuit-breakers			
Rated current = rated uninterrupted current	$I_n = I_u$	Α	32
Rated surge voltage invariability	U _{imp}		
Main contacts		V	6000
Auxiliary contacts		V	6000
Rated operational voltage	U _e	V AC	230
Overvoltage category/pollution degree	-		III/3
Rated insulation voltage	Ui	V	400
Switching capacity			
Rated short-circuit making capacity	I _{cm}		
240 V	I _{cm}	kA	55
400/415 V	I _{cm}	kA	53
440 V 50/60 Hz	I _{cm}	kA	53
Rated short-circuit breaking capacity I _{cn}		NA	30
Icu to IEC/EN 60947 test cycle 0-t-C0	I _{cn}	kA	
			25
240 V 50/60 Hz	I _{cu}	kA	25
400/415 V 50/60 Hz	I _{cu}	kA	25
Ics to IEC/EN 60947 test cycle 0-t-C0-t-C0	lcs	kA	
240 V 50/60 Hz	I _{cs}	kA	25
400/415 V 50/60 Hz	I _{cs}	kA	25
440 V 50/60 Hz	I _{cs}	kA	18.5
			Maximum back-up fuse, if the expected short-circuit currents at the installation location exceed the switching capacity of the circuit-breaker.
Utilization category to IEC/EN 60947-2			A
Lifespan, mechanical(of which max. 50 % trip by shunt/undervoltage release)	Operations		20000
Lifespan, electrical			
Max. operating frequency		Ops/h	120
Total break time at short-circuit		ms	< 10
Terminal capacity			
Standard equipment			Box terminal
Optional accessories			Screw connection
Round copper conductor			
Box terminal Solid		mm ²	1 x (10 - 16) 2 x (6 - 16)
Stranded		mm ²	1 x (10 - 70) ³⁾ 2 x (6-25)
Tunnel terminal			³⁾ Up to 95 mm² can be connected depending on the cable manufacturer.

Solid		2	1 x 16
		mm ²	1 \ 10
Stranded			
1-hole		mm ²	1 x (25 - 95)
Bolt terminal and rear-side connection			
Direct on the switch			
Solid		mm ²	1 x (10 - 16) 2 x (6 - 16)
Stranded		mm ²	1 x (10 - 70) ³⁾ 2 x 25
			$^{3)}\mathrm{Up}$ to 95 $\mathrm{mm^2}\mathrm{can}$ be connected depending on the cable manufacturer.
Al circular conductor			
Tunnel terminal			
Solid		mm^2	1 x 16
Stranded			
Stranded		mm ²	1 x (25 - 95)
Cu strip (number of segments x width x segment thickness)			
Box terminal			
	min.	mm	2 x 9 x 0.8
	max.	mm	9 x 9 x 0.8
Copper busbar (width x thickness)	mm		
Bolt terminal and rear-side connection			
Screw connection			M6
Direct on the switch			
	min.	mm	12 x 5
	max.	mm	16 x 5
Control cables			
		mm ²	1 x (0.75 - 2.5) 2 x (0.75 - 1.5)

Design verification as per IEC/EN 61439

Design verification as per IEC/EN 61439			
Technical data for design verification			
Rated operational current for specified heat dissipation	In	Α	32
Equipment heat dissipation, current-dependent	P_{vid}	W	3.17
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	70
IEC/EN 61439 design verification			
10.2 Strength of materials and parts			
10.2.2 Corrosion resistance			Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures			Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat			Meets the product standard's requirements.
10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects			Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation			Meets the product standard's requirements.
10.2.5 Lifting			Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact			Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions			Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES			Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances			Meets the product standard's requirements.
10.5 Protection against electric shock			Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components			Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections			Is the panel builder's responsibility.
10.8 Connections for external conductors			Is the panel builder's responsibility.
10.9 Insulation properties			
10.9.2 Power-frequency electric strength			Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage			Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material			Is the panel builder's responsibility.

10.10 Temperature rise	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 7.0

Low-voltage industrial components (EG000017) / Power circuit-breaker for trafo/generator/installation protection (EC000228)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Circuit breaker for power transformer, generator and system protection (ecl@ss10.0.1-27-37-04-09 [AJZ716013])

Rated permanent current lu A 32 Rated voltage V 20-230 Rated short-circuit breaking capacity lua 400 V,50 Hz A 25 Overload release current setting A 32-32 Adjustment range short-term delayed short-circuit release A 30-30 Adjustment range undelayed short-circuit release A 30-30 Adjustment range undelayed short-circuit release A 30-30 Rutegrated earth fault protection B A 30-30 Type of electrical connection of main circuit B No No Device construction Built-in device fixed built-in technique A 10-20 Under of Juxili (top hat rail) mounting optional B No 9 10-20 10	protection (coresisted)		
Rated short-circuit breaking capacity lou at 400 V, 50 Hz Overload release current setting Adjustment range short-term delayed short-circuit release Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-circuit release Adjustment range undelayed short-circuit release Adjustment range undelayed short-circuit release Integrated earth fault protection Type of electrical connection of main circuit Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as change-over contact With switched-off indicator With switched-off indicator Number of poles Number of poles Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional	Rated permanent current lu	А	32
Overload release current setting Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-circuit release Adjustment range undelayed short-circuit release Integrated earth fault protection Type of electrical connection of main circuit Period electrical connection of main circuit Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Vifth switched-off indicator Number of poles Number of poles Number of poles Number of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional	Rated voltage	V	230 - 230
Adjustment range short-term delayed short-circuit release Adjustment range undelayed short-circuit release Adjustment range undelayed short-circuit release Integrated earth fault protection No Type of electrical connection of main circuit Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as shange-over contact Nith switched-off indicator No	Rated short-circuit breaking capacity Icu at 400 V, 50 Hz	kA	25
Adjustment range undelayed short-circuit release Integrated earth fault protection Type of electrical connection of main circuit Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of fundicator With switched-off indicator With switched-off indicator Number of poles Control element Complete device with protection unit Motor drive integrated Motor drive optional	Overload release current setting	А	32 - 32
Integrated earth fault protection Type of electrical connection of main circuit Prame clamp Built-in device fixed built-in technique Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional No No Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact No Vith switched-off indicator No Vith under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Notor drive integrated No Notor drive optional	Adjustment range short-term delayed short-circuit release	А	0 - 0
Type of electrical connection of main circuit Prame clamp Built-in device fixed built-in technique No Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional No Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact No With switched-off indicator With under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional	Adjustment range undelayed short-circuit release	А	340 - 340
Device construction Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional No Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact With switched-off indicator With under voltage release No Number of poles I Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional	Integrated earth fault protection		No
Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of pulse No No No Number of poles 1 Position of connection for main current circuit Type of control element Complete device with protection unit Notor drive integrated No	Type of electrical connection of main circuit		Frame clamp
DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact With switched-off indicator No With under voltage release No Number of poles 1 Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated No Motor drive optional	Device construction		Built-in device fixed built-in technique
Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact No With switched-off indicator With under voltage release No No Number of poles 1 Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated No Motor drive optional O O No No No No No No No No	Suitable for DIN rail (top hat rail) mounting		No
Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact O With switched-off indicator With under voltage release No Number of poles 1 Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional O O No No No No No No No No	DIN rail (top hat rail) mounting optional		No
Number of auxiliary contacts as change-over contact With switched-off indicator With under voltage release No Number of poles 1 Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional O No No No No No No No No No	Number of auxiliary contacts as normally closed contact		0
With switched-off indicator With under voltage release No Number of poles Number of connection for main current circuit Type of control element Complete device with protection unit Motor drive optional No No No No No No No No No N	Number of auxiliary contacts as normally open contact		0
With under voltage release No Number of poles 1 Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive optional No No No	Number of auxiliary contacts as change-over contact		0
Number of poles 1 Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive optional 1 Front side Rocker lever Rocker lever No No	With switched-off indicator		No
Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive optional Front side Rocker lever Yes No No	With under voltage release		No
Type of control element Complete device with protection unit Motor drive optional Rocker lever Yes No No	Number of poles		1
Complete device with protection unit Yes Motor drive integrated No Motor drive optional No	Position of connection for main current circuit		Front side
Motor drive integrated No Motor drive optional No	Type of control element		Rocker lever
Motor drive optional No	Complete device with protection unit		Yes
	Motor drive integrated		No
Degree of protection (IP)	Motor drive optional		No
	Degree of protection (IP)		IP20

Characteristics

Let-through current

Let-through energy

Additional product information (links)

Weight	http://ecat.moeller.net/flip-cat/?edition=HPLEN&startpage=17.171
Temperature dependency, Derating	http://ecat.moeller.net/flip-cat/?edition=HPLEN&startpage=17.172
Effective power loss	http://ecat.moeller.net/flip-cat/?edition=HPLEN&startpage=17.174
CurveSelect characteristics program	http://www.eaton.eu/DE/Europe/Electrical/CustomerSupport/ConfigurationTools/CharacteristicsProgram/index.htm
additional technical information for NZM power switch	https://es-assets.eaton.com/DOCUMENTATION/PDF/nzm_technic_de_en.pdf