



**Signalling switch tripped, 2W**

**Part no.** IZMX-OTS16-1  
**Catalog No.** 184117  
**Alternate Catalog No.** 67C2824G42  
**EL-Nummer (Norway)** 0004398480

**Delivery program**

Product range		Accessories
Accessories		Trip indication / Reset options
Accessories		Trip-indicating auxiliary switch
		"Triggered" signaling contact with two changeover contacts
For use with		IZMX16...
<b>Instructions</b>		The retrofit kit includes the required SEC control cable terminals.

**Technical data**

**Rated breaking capacity**

Inductive load			
250 V AC		A	10
125 V DC		A	0.5
250 V DC		A	0.25

**Design verification as per IEC/EN 61439**

Technical data for design verification			
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	70

**Technical data ETIM 7.0**

Low-voltage industrial components (EG000017) / Auxiliary contact block (EC000041)			
Electric engineering, automation, process control engineering / Low-voltage switch technology / Component for low-voltage switching technology / Auxiliary switch block (ecI@ss10.0.1-27-37-13-02 [AKN342013])			
Number of contacts as change-over contact			2
Number of contacts as normally open contact			0
Number of contacts as normally closed contact			0
Number of fault-signal switches			
Rated operation current I <sub>e</sub> at AC-15, 230 V		A	10
Type of electric connection			Flat plug-in connection
Model			Integrable
Mounting method			Other
Lamp holder			