



Signalling switch tripped, 2W

Part no. IZMX-OTS40-1
Catalog No. 184118
Alternate Catalog No. 67C2824G43
EL-Nummer (Norway) 4398481

Delivery program

| | | |
|---------------------|--|---|
| Product range | | Accessories |
| Accessories | | Trip indication / Reset options |
| Accessories | | Trip-indicating auxiliary switch |
| | | "Triggered" signaling contact with two changeover contacts |
| For use with | | IZMX40... |
| Instructions | | The retrofit kit includes the required SEC control cable terminals. |

Technical data

Rated breaking capacity

| | | | |
|----------------|--|---|------|
| Inductive load | | | |
| 250 V AC | | A | 10 |
| 125 V DC | | A | 0.5 |
| 250 V DC | | A | 0.25 |

Design verification as per IEC/EN 61439

| | | | |
|--|--|----|-----|
| Technical data for design verification | | | |
| Operating ambient temperature min. | | °C | -25 |
| Operating ambient temperature max. | | °C | 70 |

Technical data ETIM 7.0

| | | | |
|--|--|---|-------------------------|
| Low-voltage industrial components (EG000017) / Auxiliary contact block (EC000041) | | | |
| Electric engineering, automation, process control engineering / Low-voltage switch technology / Component for low-voltage switching technology / Auxiliary switch block (ecI@ss10.0.1-27-37-13-02 [AKN342013]) | | | |
| Number of contacts as change-over contact | | | 2 |
| Number of contacts as normally open contact | | | 0 |
| Number of contacts as normally closed contact | | | 0 |
| Number of fault-signal switches | | | |
| Rated operation current I _e at AC-15, 230 V | | A | 10 |
| Type of electric connection | | | Flat plug-in connection |
| Model | | | Integrable |
| Mounting method | | | Other |
| Lamp holder | | | |