



Closing release 24 VDC

Part no. IZMX-SR24DC-1
Catalog No. 184281
Alternate Catalog No. 67C2822G63
EL-Nummer (Norway) 4398624

Delivery program

Product range			Accessories
Accessories			Remote switching
Accessories			closing release
			Can be combined with a shunt release and an undervoltage release. Retrofitting kit
Maximum operating frequency	Actuations/minute		3
			Limited to 3/min due to the high pick-up current for 35 ms. Please note - the circuit-breaker's switching frequency = 60/h
Rated control voltage	U_S	V	24 V DC
Operating range	$x U_S$	Factor	0,85 - 1,1
max. pick-up current (35ms)	I_n	A	19
max. pull-in power (35ms)	AC/DC	VA/W	500
Circuit-breaker total switching time	@ $U_S=100\%$	ms	30 (IZMX16..., INX16...) 35 (IZMX40..., INX40...)
For use with			IZMX16..., IZMX40... INX16..., INX40...
Instructions			The retrofit kit includes the required SEC control cable terminals.

Design verification as per IEC/EN 61439

Technical data for design verification			
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	70

Technical data ETIM 7.0

Low-voltage industrial components (EG000017) / Shunt release (for power circuit breaker) (EC001023)			
Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Full load current trip (ecl@ss10.0.1-27-37-04-18 [AKF016013])			
Rated control supply voltage U_s at AC 50HZ		V	0 - 0
Rated control supply voltage U_s at AC 60HZ		V	0 - 0
Rated control supply voltage U_s at DC		V	24 - 24
Voltage type for actuating			DC
Initial value of the undelayed short-circuit release - setting range		A	0
End value adjustment range undelayed short-circuit release		A	0
Type of electric connection			Flat plug-in connection
Number of contacts as normally open contact			0
Number of contacts as normally closed contact			0
Number of contacts as change-over contact			0
Suitable for power circuit breaker			Yes
Suitable for off-load switch			Yes
Suitable for motor safety switch			No
Suitable for overload relay			No